

Product Code: CL011B

Description: 10AX 1 Gang 2 Way Plate Switch (No Knockouts)



**General Information**

|   |   |  |
|---|---|--|
| <b>Dimensions (mm)</b>                        | 80 (W) x 80 (H) x 42 (D)  |  |
| <b>Plate Fixing Centres - Horizontal (mm)</b> | 60.3  |  |
| <b>MiniGrid Plate (Gang)</b>                  | 1   |  |
| <b>MiniGrid Single Width Module Quantity</b>  | 1   |  |
| <b>MiniGrid Double Width Module Quantity</b>  | 0   |  |
| <b>Style</b>                                  | Metal Clad  |  |
| <b>Finish</b>                                 | Metal Clad Grey   |  |
| <b>Insert Colour</b>                          | White (WH)  |  |
| <b>Materials</b>                              | Front Plate & Mounting Box:<br>Electrophoretically Coated Steel | Insert & Rocker Switch: Urea             |
|   | Rear Housing: Nylon   | Terminals: Brass                         |
|   | Terminal Screws: Steel & Yellow Passivated                      | Contacts: Silver "on-lay" Copper / Brass |
|   | Internal Busbars: Formed Pressed Brass                          | Earth Strap: Mild Steel                  |
| <b>Rated Voltage (V~) (Ue)</b>                | 250   | <b>Frequency (Hz)</b> 50                 |
| <b>Inductive Load Rating (AX)</b>             | 10  |  |
| <b>Load Rating Comments</b>                   | Suitable for Inductive Loads                                    |  |
| <b>Termination Type</b>                       | Screw   |  |
| <b>Terminal Size (mm)</b>                     | Ø3.5  | <b>Terminal Torque Value (Nm)</b> 0.5    |
| <b>Terminal Capacity - Solid (mm²)</b>        | 4 x 1.5 or 2 x 2.5  |  |
| <b>Modular Rocker Switches</b>                | Yes   |  |
| <b>2 Way Switch</b>                           | Yes   |  |
| <b>Supplied Back Box Depth (mm)</b>           | 40  |  |
| <b>Back Box Knockouts - Total (mm)</b>        | None  |  |
| <b>Back Box Earth Terminal Supplied</b>       | Yes   |  |
| <b>Operational Temperature (°C)</b>           | -5 to +40   |  |
| <b>Warranty (Years)</b>                       | 10  |  |

**Additional Information**

For cleaning / polishing of products, use only a soft, dry, clean cloth. Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal. Interchangeable with modules in the MiniGrid Range. Module colour to match is Click White (WH)

